

Enjoy listening to MP3/WMA files on CD or directly from your iPod® or Walkman® player plugged in to the front aux input of your Sony® CDX-GT360MP car stereo receiver. It's SiriusXM™ satellite radio connector¹ ready, plus experience great sound quality from the built-in equalizer and powerful 52x4 high power amplifier.



Bullets

- Detach face with LCD display and front aux input
- MP3/WMA music file playback
- SiriusXM™ Satellite radio connector ready¹
- EQ3 Stage 2 and 52 Watts x 4 high power amplifier
- 2 Volt rear/sub selectable preamp outputs with HPF/LPF
- Radio Data System (RDS)
- Convenient wireless remote (RM-X201)
- Red key illumination

Features

Detach face with front aux input

The easy-to-read single line LCD display shows clock, station ID and track data when playing back your digital MP3/WMA files. Front auxiliary input lets you connect almost any portable audio device to your car's sound system.

MP3/WMA music playback

Play CDs, CD-Rs, and CD-RWs, including discs loaded with digital MP3s and WMA files.

SiriusXM™ Satellite radio¹

The on-board SiriusXM™ connector¹ simplifies satellite radio installation by eliminating compatibility issues and provides direct connection to the new platform of tuners.

Internal high power and EQ

The CDX-GT360MP delivers 52 watts of peak power to all four speakers for powerful output (208 watts total power). The 3 band EQ3 allows users to customize the sound centered at 60 Hz, 1000 Hz and 10 kHz frequencies.

RCA outputs for external amplifiers

When you're ready to expand your sound system, the CDX-GT360MP offers selectable rear or subwoofer pre-amp RCA outputs for external amplifiers. Set the built in electronic HPF/LPF crossovers to improve sound quality and reduce system distortion.

Radio Data System

Radio Data System (RDS) feature displays radio broadcast information such as artist and track information when listening to compatible AM/FM stations. RDS also allows expanded channel playback with compatible radio station broadcasts.

Wireless card remote

Control your receiver while keeping your eyes on the road with the included wireless card remote (RM-X201).

Key illumination

Blue key illumination helps you locate buttons quickly during evening playback.

Specifications

Amplifier Section

| | |
|------------------|---|
| Max power output | 52 watts x 4 at 4 ohms |
| Power Ad Hoc | CEA2006 Standard Power: 17 Watts RMS per channel into 4 Ohms, 4 channels driven from 20 Hz to 20 kHz with less than 1% THD+N. |

| | |
|-------------------|----------|
| Speaker Impedance | 4-8 Ohms |
|-------------------|----------|

AMP & General Feature

| | |
|-----------------------------------|--|
| Aux-In | Yes (Front) |
| EQ | EQ3: 3 band EQ with +/- 10 dB adjustment at 60 Hz, 1 kHz and 10 kHz. |
| High Pass Filter | Selectable on/off at: 80, 100, 120, 140 or 160 Hz. |
| Loudness | Yes |
| Low Pass Filter | Selectable on/off at: 80, 100, 120, 140 or 160 Hz. |
| Output Power (4ohm, 1kHz, 16V)(W) | 52 watts x 4 |
| Pre Out | (1) Rear / Sub switchable |
| Rear/Sub initial | Sub |
| Sirius/XM Connector | Yes |

Audio

| | |
|----------------------------|---|
| Band | AM / FM |
| Equalizer | EQ3:3 band EQ with +/- 10 dB adjustment at 60 Hz, 1 kHz and 10 kHz. |
| Format(s) Supported | MP3/WMA files |
| Preout Impedance | 220 ohms |
| Preout Voltage | 2 volt |
| S/N Ratio | Audio Power: CEA2006 S/N 80 dBA |
| Signal-to-Noise Ratio (dB) | CD: 120 dB |
| Station Preset(s) | 18 FM / 12 AM |
| Tuner Frequency Range | FM (MHz): 87.5-107.9 AM (kHz): 530-1710 |
| Tuner Type | SSIR-EXA with RDS |
| Wow and Flutter | Below measurable limit |

AUX in Feature

| | |
|------------------|--------------------|
| Level Adjustment | Yes (-8dB / +18dB) |
|------------------|--------------------|

Convenience

| | |
|------------|----------------------|
| Tilt Range | 0-45° mounting angle |
|------------|----------------------|

Convenience Features

| | |
|------------------|--------|
| Dimmer Adjust | Manual |
| Key Illumination | Blue |
| On-Screen Clock | 12H |

Display

| | |
|--------------------|--|
| Display Color | Black / Negative Color |
| Display Technology | LCD |
| Text Displayed | Source, artist, track, playback time, menu and clock |
| Text Lines | 1 line of information |

Display Panel

| | |
|---------------|--------|
| Auto off mode | Yes |
| Dimmer Adjust | Manual |

Panel Design

| | |
|--|------------------------|
| Display color (Color Variation/Nega or Posi) | Black color / Negative |
| Display Device (LCD/FL/OEL/TFT) | LCD |
| Key Illumination | Blue |

| | |
|--------------------|--------------|
| Panel finish color | Black (Bare) |
|--------------------|--------------|

General

| | |
|---|----------------|
| CEA2006 output power | 17 |
| CEA2006 S/N | 80 |
| Dimensions (WxHxD) (mm) | 178x50x180 |
| Maximum output power (4ohm, 1kHz, 16V)(W) | 52 |
| Mounting dimensions (WxHxD)(mm) | 182 x 53 x 162 |
| Preout impedance (ohms) | 220 |
| Preout output level (V) | 2 |
| Weight (kg) | 1.2 |

Inputs and Outputs

| | |
|-----------------------|--|
| 12V Trigger Output(s) | Power amplifier turn on |
| Antenna Terminal(s) | AM/FM Antenna Input Terminal |
| Audio In | Front Aux in with variable level SiriusXM connector |
| Infrared Port | Wireless remote |
| RCA Audio Output(s) | Rear/Subwoofer selectable RCA pre-amp outputs |
| Remote Jack | Optional wired remote terminal |

Other Features

| | |
|-----------------------------|------------|
| Card Remote (): Option | RM-X201 |
| CD lock mode | Yes |
| Clock | 12H |
| Rotary commander ():Option | (RM-X4S) |
| Security | Detachable |

Tuner

| | |
|---|------------------|
| FM Usable Sensitivity | 8 dBf |
| Frequency Response | FM: 20-15,000 Hz |
| S/N Ratio | 80 dB (stereo) |
| Selectivity | 75 dB at 400 kHz |
| Stereo Separation | 50 dB at 1 KHz |
| FM: Channel separation (dB) | 50 dB at 1 kHz |
| FM: Frequency response (Hz) | 20 - 15k |
| FM: Intermediate frequency (MHz) | 25KHz |
| FM: S/N ratio (mono) (dB) | 80 dB stereo |
| FM: Selectivity (400 kHz) (dB) | 75 dB |
| FM: Tuning range (MHz) | 87.5-107.9 |
| FM: Usable sensitivity (75 ohm) (dBf) | 8 dBf |
| MW: Tuning range(kHz) | 530-1710 |
| MW/LW/SW: Sensitivity (75 ohm) MW/LW/SW(uV) | 26/-/- |

Tuner Feature

| | |
|------------------------------------|------------|
| Preset | FM18/AM12 |
| RDS/EON (NA Only:RBDS, Others:RDS) | Yes (RBDS) |

Weights and Measurements

| | |
|----------------------|---|
| Dimensions (Approx.) | 178 x 50 x 180 mm, 7.125 x 2 x 7.125 inch (w/h/d) |
|----------------------|---|

| | |
|----------------------------|-----------------------|
| Dimensions (Approx) Depth | 7.125" (180 mm) |
| Dimensions (Approx) Height | 2" (50 mm) |
| Dimensions (Approx) Width | 7.125" (178 mm) |
| Weight (Approx.) | 1.2 kg (2 lb. 11 oz.) |

Supplied Accessories

| | |
|----------------------|---|
| Supplied Accessories | Parts for installation and connections (1 set) RM-X201 wireless remote |
|----------------------|---|



1. Requires antenna and tuner, both sold sep.

© 2011 Sony Electronics Inc. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Sony, Walkman, and their respective logos are trademarks of Sony. iPod is a trademark of Apple Inc. All other trademarks are trademarks of their respective owners. Features and specifications are subject to change without notice. Updated: September 8, 2011